higher education & training

Department:
Higher Education and Training
REPUBLIC OF SOUTH AFRICA

T490**(E)**(A15)T

## NATIONAL CERTIFICATE

# MULTI-DISCIPLINARY DRAWING OFFICE PRACTICE: ELECTRICAL DRAUGHTING

(8080625)

**15 April 2019 (X-Paper)**
**09:00–13:00**

**REQUIREMENTS: Drawing sheets**

**Calculators, drawing instruments and computer-aided draughting equipment and related software may be used.**

**This question paper consists of 6 pages and 1 diagram sheet.**

Copyright reserved

# DEPARTMENT OF HIGHER EDUCATION AND TRAINING
# REPUBLIC OF SOUTH AFRICA

NATIONAL CERTIFICATE
MULTI-DISCIPLINARY DRAWING OFFICE PRACTICE:
ELECTRICAL DRAUGHTING
TIME: 4 HOURS
MARKS: 100

---

**INSTRUCTIONS AND INFORMATION**

1. Answer ALL the questions (theory and drawings) on the DRAWING SHEETS.

2. Read ALL the questions carefully.

3. Number the answers according to the numbering system used in this question paper.

4. Marks will be allocated for:

   4.1 Balanced layout and size
   4.2 Correctness
   4.3 Lettering
   4.4 Line work and neatness

5. Work neatly.

---

Copyright reserved 

## QUESTION 1: GENERAL THEORY

1.1 You are involved in the calculation of the total required flux for a new training room.

The following data is available:

| | |
|---|---|
| Recommended illuminance | 500 lm/m² |
| Coefficient of utilisation | 0,54 |
| Lamp lumen depreciation | 0,8 |
| Maintenance factor | 0,8 |
| Length of the room | 10 m |
| Width of the room | 7 m |

Use the given information to calculate the total required flux with the correct SI unit.

**HINT:** $\Phi = \frac{E_{av} \times A}{M \times CU \times LLD}$ (5)

1.2 Give the prescribed conductor diameters (mm²) for each of the following circuits or subcircuits as used in the wiring of premises:

1.2.1 Main supply

1.2.2 Cooking appliance (electrical stove)

1.2.3 Geyser

1.2.4 Socket outlet (power outlet)

1.2.5 Illumination

(5 × 1) (5)

**[10]**

## QUESTION 2: GRAPHICAL SYMBOLS AND ELECTRONIC DIAGRAMS

2.1 Shown below are graphical representations of electronic components.

Name and draw the correct and complete graphical symbol for each electronic component next to the question number (2.1.1–2.1.15) in the ANSWER BOOK. Use only IEC symbols.

2.1.1



2.1.2



2.1.3




2.1.4



2.1.5



2.1.6



2.1.7




2.1.8 


2.1.9 

2.1.10 

2.1.11 

2.1.12 

2.1.13 

2.1.14 

2.1.15 

[Source: *http://www.technologystudent.com/*] **[30]**

Copyright reserved 

## QUESTION 3: GENERATION AND DISTRIBUTION OF ELECTRICITY

The DIAGRAM SHEET (attached) shows a half-sectional front view of a porcelain insulator and an outside view of a single LT tubular cross-arm with an M12 stud, square 30 × 30 × 5 mm washer, spring washer and M12 nut.

Draw a full-sectional front view of the assembling of ALL given components to show how the insulator is attached to the LT tubular cross-arm. Label only the different components. **[25]**

## QUESTION 4: ELECTRICAL MOTORS AND CONTROL DEVICES

The outer stationary part of an alternating current (AC) induction motor is known as the stator and the inner rotating part is known as the rotor. The most basic type of rotor is known as a squirrel-cage rotor due to its simple construction.

Use drawing instruments to draw a neat, labelled drawing of a basic squirrel-cage rotor. Clearly show the construction of the shaft, the laminated core plates and the skewed slots. **[15]**

## QUESTION 5: WIRING OF PREMISES

Draw a plan elevation of a domestic installation and make provision for a:

- Living room
- Dining room
- Passage
- Minimum of TWO bedrooms
- Bathroom and toilet
- Single garage separated from the house with a subdistribution board


A detailed drawing of the building is NOT required. Add ALL electrical points, lighting, exterior spotlight(s) with switch(es) necessary for this type of building on the plan, taking into account ALL applicable regulations in the SANS 10142: The wiring of premises. The drawing must be accompanied by a legend (key) of the electrical installation symbols. **[20]**

**TOTAL: 100**

Copyright reserved

(8080625)

## DIAGRAM SHEET




Copyright reserved